

NITECORE®

The All-Round Flashlight Expert

MT10C User Manual

Features

- Utilizes a CREE XM-L2 U2 LED
- Maximum output up to 920 lumens
- Integrated metal micro textured reflector for optimal peripheral illumination
- Boasts a peak beam intensity of 9,000 cd and a throw distance of up to 190 meters
- Tail switch designed for tactical applications
- Side switches for brightness levels and modes adjustment
- Features intelligent memory effect
- Red LED provides constant/flashing illumination
- Displays battery voltage with red light (accurate to 0.1V)
- High efficiency constant current circuit enables maximum runtime of 170 hours
- Direct access to turbo/red light mode
- Reverse polarity protection prevents damage from incorrectly inserted batteries
- Stainless steel titanium-plated two-way clip
- Toughened ultra-clear mineral glass with anti-reflective coating
- Robust HAIII military grade hard-anodized
- Waterproof in accordance with IPX8 (two-meter submersible)
- Tail stand capability

Dimensions

Length: 3.59" (91.2mm)
 Head Diameter: 1" (25.4mm)
 Tail Diameter: 1" (25.4mm)
 Weight: 2.01oz (57g)(without battery)

Accessories

Holster, clip, lanyard, spare tailcap cover, spare O-ring, (R)CR123 battery magazine

Battery Options

	TYPE	Nominal voltage	Compatible
Primary Lithium battery	CR123	3V	Y (Recommended)
IMR18350 Rechargeable Li-ion battery	IMR18350	3.7V	Y
Rechargeable Li-ion battery	RCR123	3.7V	Y

▲ **Warning:** Rechargeable IMR Li-ion batteries are not equipped with a protective circuit. Beware of over-discharging.

Brightness & Runtime

FL1 STANDARD	TURBO	HIGH	MID	LOW	LOWER	RED LIGHT	SIGNAL LIGHT	STROBE	LOCATION	SOS	NOTICE
	920 LUMENS	500 LUMENS	180 LUMENS	70 LUMENS	1 LUMEN	0.8 LUMENS	0.8 LUMENS	920 LUMENS	920 LUMENS	920 LUMENS	The stated data has been measured in accordance with the international flashlight testing standards ANSINEMA FL1, using one high quality IMR18350 Li-ion battery (3.7V, 700mAh) under laboratory conditions.
⌚	30min	45min	1h 45min	5h	120h	23h	24h	—	—	—	
📏	190m	125m	88m	40m	5.8m	2.5m	—	—	—	—	
👁️	9000cd	4000cd	1950cd	380cd	8.5cd	1.5cd	—	—	—	—	
🛡️	1m (Impact Resistant)										
🌊	IPX8, 2m (Waterproof AND Submersible)										

FL1 STANDARD	TURBO	HIGH	MID	LOW	LOWER	RED LIGHT	SIGNAL LIGHT	STROBE	LOCATION	SOS	NOTICE
	480 LUMENS	280 LUMENS	135 LUMENS	50 LUMENS	1 LUMEN	0.8 LUMENS	0.8 LUMENS	480 LUMENS	480 LUMENS	480 LUMENS	The stated data has been measured in accordance with the international flashlight testing standards ANSINEMA FL1, using one high quality CR123 battery (3V, 1700mAh) under laboratory conditions.
⌚	45min	1h 30min	3h	8h	170h	18h	20h	—	—	—	
📏	127m	102m	67m	26m	5.8m	2.5m	—	—	—	—	
👁️	4050cd	2620cd	1110cd	175cd	8.5cd	1.5cd	—	—	—	—	
🛡️	1m (Impact Resistant)										
🌊	IPX8, 2m (Waterproof AND Submersible)										

Brightness Levels

When the MT10C is switched on, press the step-up switch repeatedly to switch from the following brightness levels: red beacon-red light-ultralow-low-medium-high-turbo. The MT10C has memory effect. When it is switched on, the MT10C will enter the brightness level last used.

When the MT10C is switched on, press the step-down switch repeatedly to lower its brightness until red beacon mode, after which there is no cycling back to other brightness levels.

Direct Access to Red Light Mode:

When the MT10C is switched on, press and hold the step-down switch for over one second to access the red light mode; OR:

When the MT10C is switched off, press and hold the step-down switch and press the button on the tailcap to access the red light mode.

Direct Access to Turbo:

When the MT10C is switched on, press and hold the step-up switch for over one second to access turbo output (920 lumens); OR:

When the MT10C is switched off, press and hold the step-up switch and press the button on the tailcap to access turbo output (920 lumens).


Note: After three minutes' using of turbo mode, the flashlight will lower its output automatically to prevent overheating, and efficiently ensure the battery runtime.

Special modes (Strobe/Location/SOS)

With the light switched on, press both side switches to enter strobe mode. When in strobe mode, press both side switches again to cycle through Location Beacon, SOS, and Strobe modes. To exit and resume the brightness level last used, simply press the step-up or step-down switch. The MT10C has memory effect in strobe mode. If it is turned off in strobe mode, it will enter strobe mode immediately when switched on again.

Power Tips

With the light switched off, press both side switches and the button on the tailcap to activate the red power indicator to blink and indicate battery voltage (accurate to 0.1V). For example, when battery voltage is at 4.2V, the red power indicator will blink 4 times, followed by a one second pause and another 2 blinks. Different voltages represent the corresponding remaining battery power levels.



Changing / Charging Battery

Battery should be replaced or recharged when output appears to be dim or the flashlight becomes unresponsive.

Maintenance

Every 6 months, threads should be wiped with a clean cloth followed by a thin coating of silicon-based lubricant.

Warranty Service

All NITECORE® products are warranted for quality. Any defective / malfunctioning NITECORE® product can be repaired free of charge for a period of 60 months (5 years) from the date of purchase. Beyond 60 months (5 years), a limited warranty applies, covering the cost of labor and maintenance, but not the cost of accessories or replacement parts.

The warranty is nullified in all of the following situations:

1. The product(s) is/are broken down, reconstructed and/or modified by unauthorized parties.
2. The product(s) is/are damaged through improper use.
3. The product(s) is/are damaged by leakage of batteries.

For the latest information on NITECORE® products and services, please contact a local NITECORE® distributor or send an email to service@nitecore.com

※All images, text and statements specified herein this user manual are for reference purpose only. Should any discrepancy occurs between this manual and information specified on www.nitecore.com, information on our official website shall prevail. Sysmax Industry Co., Ltd. reserves the rights to interpret and amend the content of this document at any time without prior notice.

Please find us on facebook: NITECORE Flashlight

SYSMAX Ind. Co., Ltd.

TEL: +86-20-83862000
 FAX: +86-20-83882723
 E-mail: info@nitecore.com
 Web: www.nitecore.com
 Address: Rm 2601-06, Central Tower, No.5 Xiancun Road, Tianhe District, Guangzhou, 510623, Guangdong, China



Thanks for purchasing NITECORE!